

THE ERROR PRINCIPLE

D M APPLEBY

Department of Physics, Queen Mary and Westfield College, Mile End Rd, London
E1 4NS, UK

(e-mail: D.M.Appleby@qmw.ac.uk)

Abstract

The problem of characterising the accuracy of, and disturbance caused by a joint measurement of position and momentum is investigated. In a previous paper the problem was discussed in the context of the unbiased measurements considered by Arthurs and Kelly. It is now shown, that suitably modified versions of these results hold for a much larger class of simultaneous measurements. The approach is a development of that adopted by Braginsky and Khalili in the case of a single measurement of position only. A distinction is made between the errors of retrodiction and the errors of prediction. Two error-error relationships and four error-disturbance relationships are derived, supplementing the Uncertainty Principle usually so-called. In the general case it is necessary to take into account the range of the measuring apparatus. Both the ideal case, of an instrument having infinite range, and the case of a real instrument, for which the range is finite, are discussed.

PACS number: 03.65.Bz

Report no. QMW-PH-98-13

1. INTRODUCTION

Heisenberg's [1] formulation of the Uncertainty Principle was one of the key steps in the development of Quantum Mechanics. Nevertheless, seventy years after the publication of his original paper, there remain a number of obscurities regarding its interpretation [2].

In contemporary discussions the Uncertainty Principle is usually identified with the statement

$$\Delta x \Delta p \geq \frac{\hbar}{2} \quad (1)$$

where Δx , Δp are the standard deviations

$$\begin{aligned} \Delta x &= \left(\langle \psi | \hat{x}^2 | \psi \rangle - \langle \psi | \hat{x} | \psi \rangle^2 \right)^{\frac{1}{2}} \\ \Delta p &= \left(\langle \psi | \hat{p}^2 | \psi \rangle - \langle \psi | \hat{p} | \psi \rangle^2 \right)^{\frac{1}{2}} \end{aligned} \quad (2)$$

In his original paper Heisenberg suggested that the quantities Δx , Δp appearing in Eq. (1) may be interpreted as experimental errors, and that the Uncertainty Principle represents a fundamental constraint on the accuracy achievable in a simultaneous measurement of position and momentum. At least, that is what he has often been taken to have suggested (Heisenberg's own phraseology is somewhat ambiguous). In the words of Bohm [3]:

If a measurement of position is made with accuracy Δx , and if a measurement of momentum is made *simultaneously* with accuracy Δp , then the product of the two errors can never be smaller than a number of order $\hbar$.

Is this a legitimate interpretation of Eq. (1)? The question has been discussed by Ballentine [4], Prugovečki [5], Busch [6], Wódkiewicz [7], Hilgevoord and Uffink [2], Raymer [8] and de Muynck *et al* [9]. The consensus seems to be, that the quantities Δx , Δp defined in Eq. (2) cannot be regarded as experimental errors because they are intrinsic properties of the isolated system. An experimental error, by contrast, should depend, not only on the state of the system, but also on the state of the apparatus, and the nature of the measurement interaction. Hilgevoord and Uffink [2] have further remarked, that in Heisenberg's microscope argument, it is only the position of the particle which is measured. Although it is true that Heisenberg alludes to the possibility of performing simultaneous measurements of position *and* momentum, such measurements form no part of his actual argument.

It follows from all this, that the statement of Bohm's just quoted cannot be identified with the Uncertainty Principle usually so-called. Rather, it represents (if true) an independent physical principle: the Error Principle, as it might be called.

The problem we now face is, that although the Error Principle as stated by Bohm is intuitively quite plausible, it cannot be regarded as rigorously established. In order to establish it two things are necessary. In the first place, we need to define precisely what is meant by the accuracy of a simultaneous measurement process. In the second place, we need to derive a bound on the accuracy, starting from the fundamental principles of Quantum Mechanics. The problem is of some interest, in view of the importance that simultaneous measurements now have in the field of quantum optics [10, 11, 12, 13, 14, 15, 16].

An approach to the problem which has attracted a good deal of attention over the years is the one based on positive operator valued measures and the concept of a “fuzzy” or “stochastic” phase space [5, 6, 9, 17, 18, 19, 20, 21]. For a recent review see Busch *et al* [16]. This approach has recently been criticised by Uffink [22].

In a previous paper [23] we adopted a rather different approach. We began with Braginsky and Khalili’s [24] analysis of single measurements of x or p by themselves, and extended it to a class of simultaneous measurement processes: namely, the class of unbiased measurement processes, for which the systematic errors are all zero. Our analysis depended on making a distinction between the retrodictive and predictive (or determinative and preparative) aspects of a measurement [2, 19, 25]. We accordingly defined two different kinds of error: the errors of retrodiction, $\Delta_{\text{ei}}x$ and $\Delta_{\text{ei}}p$, describing the accuracy with which the result of the measurement reflects the initial state of the system; and the errors of prediction, $\Delta_{\text{ef}}x$ and $\Delta_{\text{ef}}p$, describing the accuracy with which the result of the measurement reflects the final state of the system. Corresponding to these two kinds of error we derived two inequalities: a retrodictive error relationship

$$\Delta_{\text{ei}}x \Delta_{\text{ei}}p \geq \frac{\hbar}{2} \quad (3)$$

and a predictive error relationship

$$\Delta_{\text{ef}}x \Delta_{\text{ef}}p \geq \frac{\hbar}{2} \quad (4)$$

Eqs. (3) and (4) jointly comprise a precise statement of the semi-intuitive Error Principle discussed above.

Following Braginsky and Khalili we also defined two quantities $\Delta_{\text{d}}x$, $\Delta_{\text{d}}p$ describing the disturbance of the system by the measurement; and we derived the four error-disturbance relationships

$$\begin{aligned} \Delta_{\text{ei}}x \Delta_{\text{d}}p &\geq \frac{\hbar}{2} & \Delta_{\text{ef}}x \Delta_{\text{d}}p &\geq \frac{\hbar}{2} \\ \Delta_{\text{ei}}p \Delta_{\text{d}}x &\geq \frac{\hbar}{2} & \Delta_{\text{ef}}p \Delta_{\text{d}}x &\geq \frac{\hbar}{2} \end{aligned} \quad (5)$$

These relationships provide a precise statement of the principle, that a decrease in the error of the measurement of one observable can only be achieved at the cost of a corresponding increase in the disturbance of the canonically conjugate observable.

The relationships above, together with Eq. (1), comprise a total of seven inequalities, all of which are needed if one wants to capture the full intuitive content of Heisenberg’s original paper [1].

Arthurs and Kelly [10] have shown, that in the case of a retrodictively unbiased joint measurement process (*i.e.* a process for which the final state expectation values of the pointer positions coincide with the initial state expectation values of the position and momentum), one has

$$\Delta\mu_X \Delta\mu_P \geq \hbar \quad (6)$$

where the quantities on the right hand side are the final state uncertainties for the pointer positions μ_X and μ_P (also see Arthurs and Goodman [11], Wódkiewicz [7], Raymer [8] and Leonhardt and Paul [26]). In ref. [23] we showed that the Arthurs-Kelly relationship can be deduced from the retrodictive error relationship.

The unsatisfactory feature of the arguments given in ref. [23] is that they only serve to establish the above inequalities for a limited class of measurement processes. That is, we only proved Eq. (3) on the assumption that the measurement is retrodictively unbiased, and Eq. (5) on the still more restrictive assumption that the measurement is both retrodictively and predictively unbiased. Our purpose in the following is to show, that with a suitable modification of the definitions, these relationships continue to hold for a very much larger class of measurement processes.

2. SIMULTANEOUS MEASUREMENT PROCESSES

We begin by characterising the class of measurement processes which we are going to discuss.

Consider a system, with state space $\mathcal{H}_{\text{sy}}$, interacting with an apparatus, with state space $\mathcal{H}_{\text{ap}}$. The system is assumed to have one degree of freedom, with position $\hat{x}$ and momentum $\hat{p}$, satisfying the commutation relationship

$$[\hat{x}, \hat{p}] = i\hbar \quad (7)$$

The apparatus is assumed to be characterised by two pointer observables $\hat{\mu}_X$ (measuring the position of the system) and $\hat{\mu}_P$ (measuring the momentum of the system), together with n other observables $\hat{y}_1, \hat{y}_2, \dots, \hat{y}_n$. These $n + 2$ operators constitute a complete set of commuting observables describing the state of the apparatus. They also commute with the system observables $\hat{x}, \hat{p}$.

It is assumed that the system+apparatus is initially in a product state of the form $|\psi \otimes \phi_{\text{ap}}\rangle$, where $|\psi\rangle \in \mathcal{H}_{\text{sy}}$ is the initial state of the system and $|\phi_{\text{ap}}\rangle \in \mathcal{H}_{\text{ap}}$ is the initial state of the apparatus. The unitary evolution operator describing the measurement interaction will be denoted $\hat{U}$. The final state of the system+apparatus is $\hat{U}|\psi \otimes \phi_{\text{ap}}\rangle$. The probability distribution of the measured values is

$$\rho(\mu_X, \mu_P) = \int dx dy_1 \dots dy_n |\langle x, \mu_X, \mu_P, y_1, \dots, y_n | \hat{U} |\psi \otimes \phi_{\text{ap}}\rangle|^2$$

In ref. [23] we assumed that the measurement process was unbiased, so that

$$\langle \psi \otimes \phi_{\text{ap}} | \hat{U}^\dagger \hat{\mu}_X \hat{U} | \psi \otimes \phi_{\text{ap}} \rangle = \langle \psi \otimes \phi_{\text{ap}} | \hat{U}^\dagger \hat{x} \hat{U} | \psi \otimes \phi_{\text{ap}} \rangle = \langle \psi \otimes \phi_{\text{ap}} | \hat{x} | \psi \otimes \phi_{\text{ap}} \rangle$$

and

$$\langle \psi \otimes \phi_{\text{ap}} | \hat{U}^\dagger \hat{\mu}_P \hat{U} | \psi \otimes \phi_{\text{ap}} \rangle = \langle \psi \otimes \phi_{\text{ap}} | \hat{U}^\dagger \hat{p} \hat{U} | \psi \otimes \phi_{\text{ap}} \rangle = \langle \psi \otimes \phi_{\text{ap}} | \hat{p} | \psi \otimes \phi_{\text{ap}} \rangle$$

We make no such assumption here.

It may also be worth noting that we do not assume the existence of momenta canonically conjugate to the pointer observables (as is the case in the Arthurs-Kelly process [10, 12, 15], for example). In particular, we make no assumptions regarding the spectra of the pointer observables.

3. DEFINITION OF THE ERRORS AND DISTURBANCES

Let $\mathcal{O}$ be any of the Schrödinger picture operators $\hat{x}, \hat{p}, \hat{\mu}_X, \hat{\mu}_P$. Let $\mathcal{O}_i = \mathcal{O}$ be the corresponding Heisenberg picture operator at the instant the measurement interaction begins; and let $\mathcal{O}_f = \hat{U}^\dagger \mathcal{O} \hat{U}$ be the Heisenberg picture operator at the instant the interaction finishes. Define the retrodictive error operators

$$\hat{\epsilon}_{Xi} = \hat{\mu}_{Xf} - \hat{x}_i \quad \hat{\epsilon}_{Pi} = \hat{\mu}_{Pf} - \hat{p}_i \quad (8)$$

the predictive error operators

$$\hat{\epsilon}_{Xf} = \hat{\mu}_{Xf} - \hat{x}_f \quad \hat{\epsilon}_{Pf} = \hat{\mu}_{Pf} - \hat{p}_f \quad (9)$$

and the disturbance operators

$$\hat{\delta}_X = \hat{x}_f - \hat{x}_i \quad \hat{\delta}_P = \hat{p}_f - \hat{p}_i \quad (10)$$

Let $\mathcal{S}$ be the unit sphere in the system state space $\mathcal{H}_{\text{sy}}$. We then define the maximal rms errors of retrodiction

$$\begin{aligned} \Delta_{\text{ei}}x &= \sup_{|\psi\rangle \in \mathcal{S}} \left(\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{Xi}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \\ \Delta_{\text{ei}}p &= \sup_{|\psi\rangle \in \mathcal{S}} \left(\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{Pi}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \end{aligned} \quad (11)$$

the maximal rms errors of prediction

$$\begin{aligned} \Delta_{\text{ef}}x &= \sup_{|\psi\rangle \in \mathcal{S}} \left(\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{Xf}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \\ \Delta_{\text{ef}}p &= \sup_{|\psi\rangle \in \mathcal{S}} \left(\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{Pf}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \end{aligned} \quad (12)$$

and the maximal rms disturbances

$$\begin{aligned} \Delta_{\text{d}}x &= \sup_{|\psi\rangle \in \mathcal{S}} \left(\langle \psi \otimes \phi_{\text{ap}} | \hat{\delta}_X^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \\ \Delta_{\text{d}}p &= \sup_{|\psi\rangle \in \mathcal{S}} \left(\langle \psi \otimes \phi_{\text{ap}} | \hat{\delta}_P^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \end{aligned} \quad (13)$$

We discussed the physical interpretation of these quantities in ref. [23]. The reader may confirm that this interpretation continues to be valid in the present more general context.

It should be noted, that in these definitions, the supremum is only taken over all normalised initial system states. The initial apparatus state is held fixed. The quantities $\Delta_{\text{ei}}x$, $\Delta_{\text{ei}}p$, $\Delta_{\text{ef}}x$, $\Delta_{\text{ef}}p$, $\Delta_{\text{d}}x$, $\Delta_{\text{d}}p$ are therefore functions of the initial apparatus state.

It should also be noted that the definitions just given differ slightly from those in ref. [23], in that we did not previously take the supremum over all initial system states. Some such change in the definitions is essential, if the error-error and error-disturbance relationships proved in ref. [23], for the special case of unbiased measurement processes, are to be generalised, so as to apply to the larger class of processes considered in this paper. As we show in the appendix, if one drops the requirement that the measurement be unbiased, then it is possible to find processes such that, with a suitable choice of initial state $|\psi\rangle$,

$$\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{Xi}^2 | \psi \otimes \phi_{\text{ap}} \rangle \langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{Pi}^2 | \psi \otimes \phi_{\text{ap}} \rangle = 0$$

It is only when one takes the supremum over all states $|\psi\rangle$ that one gets the inequalities of Eqs. (21) and (22).

As discussed in reference [23], the quantity $(\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{Xi}^2 | \psi \otimes \phi_{\text{ap}} \rangle)^{\frac{1}{2}}$ represents the rms retrodictive error in the measurement of x when the system is initially in the state $|\psi\rangle$. The quantity $\Delta_{\text{ei}}x$ (as defined above) consequently represents the

maximum rms error obtained, when the system is allowed to range over every possible initial state. Similarly with the quantities $\Delta_{ei}p$, $\Delta_{ef}x$, $\Delta_{ef}p$, $\Delta_{d}x$, $\Delta_{d}p$.

It is easy to think of measurement interactions for which the errors and disturbances defined in Eqs. (11–13) are finite (with an appropriate choice of initial apparatus state). An example of such a process is the Arthurs-Kelly process [10, 12, 15] (see ref. [27]). In the case of the Arthurs-Kelly process $\langle \psi \otimes \phi_{ap} | \mathcal{O}^2 | \psi \otimes \phi_{ap} \rangle$, with $\mathcal{O}$ any error or disturbance operator, is independent of the state $|\psi\rangle$ —which means, that in the particular case of the Arthurs-Kelly process, the definitions of $\Delta_{ei}x$, $\Delta_{ei}p$, $\Delta_{ef}x$, $\Delta_{ef}p$, $\Delta_{d}x$, $\Delta_{d}p$ which are employed in this paper coincide with the definitions used in refs. [23, 27]). It should, however, be observed that interactions for which this is true are somewhat idealised. A real measuring instrument will have a finite range. If the initial system state expectation values $\langle \psi | \hat{x}_i | \psi \rangle$ and $\langle \psi | \hat{p}_i | \psi \rangle$ are a long way outside the range of the instrument, then the errors and disturbances may not be small. Consequently, in the case of a real measuring instrument, the quantities defined in Eqs. (11–13) may well be infinite, or at least very large. To put it another way, in the case of a real measuring instrument, these quantities do not correspond very closely to one's intuitive idea of the accuracy of and disturbance caused by a realistic measurement process. In section 7 we show how the definitions can be modified, so as to obviate this difficulty.

4. COMMUTATORS

We have, as an immediate consequence of the definitions,

$$[\hat{\epsilon}_{Xf}, \hat{\epsilon}_{Pf}] = i\hbar \quad (14)$$

The other commutators between the error and disturbance operators give more difficulty. This is because the retrodictive error and disturbance operators mix Heisenberg picture observables defined at different times. It turns out, however, that it is possible to express every remaining commutator of interest in terms of commutators between one of the operators $\hat{\epsilon}_{Xi}$, $\hat{\epsilon}_{Pi}$, $\hat{\epsilon}_{Xf}$, $\hat{\epsilon}_{Pf}$, $\hat{\delta}_X$, $\hat{\delta}_P$ and one of the operators $\hat{x}_i$, $\hat{p}_i$. The significance of this result is that $\hat{x}_i$, $\hat{p}_i$ generate translations in the system phase space.

In fact

$$\begin{aligned} [\hat{\epsilon}_{Xi}, \hat{\epsilon}_{Pi}] &= [(\hat{\mu}_{Xf} - \hat{x}_i), (\hat{\mu}_{Pf} - \hat{p}_i)] \\ &= i\hbar - [\hat{x}_i, \hat{\mu}_{Pf}] + [\hat{p}_i, \hat{\mu}_{Xf}] \\ &= i\hbar - [\hat{x}_i, (\hat{p}_i + \hat{\epsilon}_{Pi})] + [\hat{p}_i, (\hat{x}_i + \hat{\epsilon}_{Xi})] \\ &= -i\hbar - [\hat{x}_i, \hat{\epsilon}_{Pi}] + [\hat{p}_i, \hat{\epsilon}_{Xi}] \end{aligned} \quad (15)$$

Similarly

$$\begin{aligned} [\hat{\epsilon}_{Xi}, \hat{\delta}_P] &= -i\hbar - [\hat{x}_i, \hat{\delta}_P] + [\hat{p}_i, \hat{\epsilon}_{Xi}] \\ [\hat{\delta}_X, \hat{\epsilon}_{Pi}] &= -i\hbar - [\hat{x}_i, \hat{\epsilon}_{Pi}] + [\hat{p}_i, \hat{\delta}_X] \end{aligned} \quad (16)$$

and

$$\begin{aligned} [\hat{\epsilon}_{Xf}, \hat{\delta}_P] &= -i\hbar + [\hat{p}_i, \hat{\epsilon}_{Xf}] \\ [\hat{\delta}_X, \hat{\epsilon}_{Pf}] &= -i\hbar - [\hat{x}_i, \hat{\epsilon}_{Pf}] \end{aligned} \quad (17)$$

5. ERROR AND ERROR-DISTURBANCE RELATIONSHIPS

We have, as an immediate consequence of Eq. (14),

$$\Delta_{\text{ef}} x \Delta_{\text{ef}} p \geq \frac{\hbar}{2} \quad (18)$$

For the remaining relationships we have to work a little harder. Let $|\psi\rangle$ be any normalised state $\in \mathcal{H}_{\text{sy}}$. Let

$$\hat{D}_{xp} = \exp \left[\frac{i}{\hbar} (p\hat{x} - x\hat{p}) \right]$$

be the system phase space displacement operator, and define

$$|\psi_{xp}\rangle = \hat{D}_{xp} |\psi\rangle$$

We have

$$\begin{aligned} i\hbar \frac{\partial}{\partial x} \hat{D}_{xp} &= (\hat{p} - \tfrac{1}{2}p) \hat{D}_{xp} & -i\hbar \frac{\partial}{\partial x} \hat{D}_{xp}^\dagger &= \hat{D}_{xp}^\dagger (\hat{p} - \tfrac{1}{2}p) \\ -i\hbar \frac{\partial}{\partial p} \hat{D}_{xp} &= (\hat{x} - \tfrac{1}{2}x) \hat{D}_{xp} & i\hbar \frac{\partial}{\partial p} \hat{D}_{xp}^\dagger &= \hat{D}_{xp}^\dagger (\hat{x} - \tfrac{1}{2}x) \end{aligned}$$

In view of Eq. (15) we then have

$$\langle \psi_{xp} \otimes \phi_{\text{ap}} | [\hat{\epsilon}_{\text{Xi}}, \hat{\epsilon}_{\text{Pi}}] | \psi_{xp} \otimes \phi_{\text{ap}} \rangle = -i\hbar (1 + \nabla \cdot \mathbf{v}) \quad (19)$$

where $\mathbf{v}$ is the vector

$$\mathbf{v} = \begin{pmatrix} \langle \psi_{xp} \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xi}} | \psi_{xp} \otimes \phi_{\text{ap}} \rangle \\ \langle \psi_{xp} \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pi}} | \psi_{xp} \otimes \phi_{\text{ap}} \rangle \end{pmatrix}$$

and ∇ is the phase space gradient operator

$$\nabla = \begin{pmatrix} \frac{\partial}{\partial x} \\ \frac{\partial}{\partial p} \end{pmatrix}$$

Now consider the box-shaped region $\mathcal{R}$ in phase space, with vertices at $(\frac{L}{2}, \frac{P}{2})$, $(-\frac{L}{2}, \frac{P}{2})$, $(-\frac{L}{2}, -\frac{P}{2})$, $(\frac{L}{2}, -\frac{P}{2})$. Let $\mathcal{C}$ be its boundary. We have

$$\begin{aligned} \Delta_{\text{ei}} x \Delta_{\text{ei}} p &\geq \frac{1}{2LP} \int_{\mathcal{R}} dx dp |\langle \psi_{xp} \otimes \phi_{\text{ap}} | [\hat{\epsilon}_{\text{Xi}}, \hat{\epsilon}_{\text{Pi}}] | \psi_{xp} \otimes \phi_{\text{ap}} \rangle| \\ &\geq \frac{1}{2LP} \left| \int_{\mathcal{R}} dx dp \langle \psi_{xp} \otimes \phi_{\text{ap}} | [\hat{\epsilon}_{\text{Xi}}, \hat{\epsilon}_{\text{Pi}}] | \psi_{xp} \otimes \phi_{\text{ap}} \rangle \right| \\ &\geq \frac{\hbar}{2} \left(1 - \frac{1}{LP} \left| \int_{\mathcal{R}} dx dp \nabla \cdot \mathbf{v} \right| \right) \\ &= \frac{\hbar}{2} \left(1 - \frac{1}{LP} \left| \int_{\mathcal{C}} ds \mathbf{n} \cdot \mathbf{v} \right| \right) \\ &\geq \frac{\hbar}{2} \left(1 - \frac{2}{L} \Delta_{\text{ei}} x - \frac{2}{P} \Delta_{\text{ei}} p \right) \end{aligned} \quad (20)$$

where ds is the line element and $\mathbf{n}$ is the outward-pointing unit normal along $\mathcal{C}$. Taking the limit as $L, P \rightarrow \infty$ we deduce

$$\Delta_{\text{ei}} x \Delta_{\text{ei}} p \geq \frac{\hbar}{2} \quad (21)$$

whenever the left hand side is defined (*i.e.* whenever it is not of the form $0 \times \infty$).

Starting from Eqs. (16) and (17) we deduce, by essentially the same argument,

$$\begin{aligned}\Delta_{\text{ei}}x \Delta_{\text{d}}p &\geq \frac{\hbar}{2} & \Delta_{\text{ef}}x \Delta_{\text{d}}p &\geq \frac{\hbar}{2} \\ \Delta_{\text{ei}}p \Delta_{\text{d}}x &\geq \frac{\hbar}{2} & \Delta_{\text{ef}}p \Delta_{\text{d}}x &\geq \frac{\hbar}{2}\end{aligned}\tag{22}$$

whenever the products are defined.

It should be noted, that although the relationships proved in this section have the same form as the corresponding relationships proved in ref. [23], they do not have the same content, since the quantities $\Delta_{\text{ei}}x$, $\Delta_{\text{ei}}p$, $\Delta_{\text{ef}}x$, $\Delta_{\text{ef}}p$, $\Delta_{\text{d}}x$, $\Delta_{\text{d}}p$ appearing in them are not defined in the same way (in ref. [23] we did not take a supremum over all normalised initial system states when defining the errors and disturbances. See Section 3 above, and Section 6 immediately following).

In the Introduction we remarked, that in the case of the retrodictively unbiased measurement processes considered in ref. [23], the Arthurs-Kelly relationship [Eq. (6) above] is a consequence of the retrodictive error relationship. It is an interesting question, which we have not as yet been able to resolve, whether it is possible to deduce an Arthurs-Kelly type bound from Eq. (21), applying to the much more general class of measurement processes considered in this paper.

6. UNBIASED MEASUREMENTS

Suppose that the measurement process is retrodictively unbiased, in the sense that

$$\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xi}} | \psi \otimes \phi_{\text{ap}} \rangle = \langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pi}} | \psi \otimes \phi_{\text{ap}} \rangle = 0$$

uniformly, for all $|\psi\rangle \in \mathcal{H}_{\text{sy}}$ (but fixed $|\phi_{\text{ap}}\rangle$). Then the vector $\mathbf{v}$ appearing on the right hand side of Eq. (19) is identically zero, and we have

$$\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \geq \frac{\hbar^2}{4}$$

uniformly, for all $|\psi\rangle \in \mathcal{H}_{\text{sy}}$.

Suppose, in addition, that the measurement is predictively unbiased:

$$\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xf}} | \psi \otimes \phi_{\text{ap}} \rangle = \langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pf}} | \psi \otimes \phi_{\text{ap}} \rangle = 0$$

for all $|\psi\rangle$. Then we have, by a similar argument,

$$\begin{aligned}\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \langle \psi \otimes \phi_{\text{ap}} | \hat{\delta}_{\text{P}}^2 | \psi \otimes \phi_{\text{ap}} \rangle &\geq \frac{\hbar^2}{4} \\ \langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xf}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \langle \psi \otimes \phi_{\text{ap}} | \hat{\delta}_{\text{P}}^2 | \psi \otimes \phi_{\text{ap}} \rangle &\geq \frac{\hbar^2}{4} \\ \langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \langle \psi \otimes \phi_{\text{ap}} | \hat{\delta}_{\text{X}}^2 | \psi \otimes \phi_{\text{ap}} \rangle &\geq \frac{\hbar^2}{4} \\ \langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pf}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \langle \psi \otimes \phi_{\text{ap}} | \hat{\delta}_{\text{X}}^2 | \psi \otimes \phi_{\text{ap}} \rangle &\geq \frac{\hbar^2}{4}\end{aligned}$$

uniformly, for all $|\psi\rangle$.

These are the results which we proved in ref. [23] by a different method.

7. MEASUREMENTS WITH A FINITE RANGE

Real measuring instruments are only designed to be used for a limited set of initial system states. For such an instrument one expects the maximal rms errors and disturbances defined in Eqs. (11–13) to be infinite, or at least very large. This is because the supremum is taken over every possible initial system state, including those states for which the expected values of $\hat{x}$ and $\hat{p}$ are far outside the range of the instrument. It follows that the quantities defined in Eqs. (11–13) are poor indicators of the accuracies and disturbances to be expected when the instrument is used in the manner in which it was designed to be used. In the case of a real measuring instrument, what interests us are the maximum errors and disturbances obtained for a *limited class* of initial system states—namely, the class on which the instrument was designed to make measurements. In this section we discuss an alternative definition of the errors and disturbances which is more appropriate to such a case.

Suppose that the instrument is designed to be accurate for initial system states $|\psi\rangle$ such that

$$x_0 - \frac{1}{2}L \leq \langle\psi|\hat{x}|\psi\rangle \leq x_0 + \frac{1}{2}L \quad p_0 - \frac{1}{2}P \leq \langle\psi|\hat{p}|\psi\rangle \leq p_0 + \frac{1}{2}P$$

and

$$\Delta x \leq \sigma \quad \Delta p \leq \tau$$

for fixed constants $x_0, p_0, L, P, \sigma, \tau$ such that $\sigma\tau \geq \frac{\hbar}{2}$. Let $\mathcal{S}'$ be the set of normalised states $\in \mathcal{H}_{\text{sy}}$ which satisfy these conditions. The errors and disturbances appropriate for the description of this instrument are obtained by taking the supremum over all normalised states $|\psi\rangle \in \mathcal{S}'$:

$$\Delta'_{\text{ei}}x = \sup_{|\psi\rangle \in \mathcal{S}'} \left(\langle\psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \quad (23)$$

$$\Delta'_{\text{ei}}p = \sup_{|\psi\rangle \in \mathcal{S}'} \left(\langle\psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}}$$

$$\Delta'_{\text{ef}}x = \sup_{|\psi\rangle \in \mathcal{S}'} \left(\langle\psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xf}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \quad (24)$$

$$\Delta'_{\text{ef}}p = \sup_{|\psi\rangle \in \mathcal{S}'} \left(\langle\psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pf}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}}$$

$$\Delta'_{\text{d}}x = \sup_{|\psi\rangle \in \mathcal{S}'} \left(\langle\psi \otimes \phi_{\text{ap}} | \hat{\delta}_{\text{X}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}} \quad (25)$$

$$\Delta'_{\text{d}}p = \sup_{|\psi\rangle \in \mathcal{S}'} \left(\langle\psi \otimes \phi_{\text{ap}} | \hat{\delta}_{\text{P}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \right)^{\frac{1}{2}}$$

It follows from Eq. (14)

$$\Delta'_{\text{ef}}x \Delta'_{\text{ef}}p \geq \frac{\hbar}{2}$$

Turning to the retrodictive error relationship, let $|\psi\rangle$ be any normalised state $\in \mathcal{H}_{\text{sy}}$ such that

$$\langle\psi|\hat{x}|\psi\rangle = x_0 \quad \langle\psi|\hat{p}|\psi\rangle = p_0$$

and

$$\Delta x \leq \sigma \qquad \Delta p \leq \tau$$

Let $\mathcal{R}$ be the box-shaped region of phase space with vertices $(x_0 + \frac{L}{2}, p_0 + \frac{P}{2})$, $(x_0 - \frac{L}{2}, p_0 + \frac{P}{2})$, $(x_0 - \frac{L}{2}, p_0 - \frac{P}{2})$, $(x_0 + \frac{L}{2}, p_0 - \frac{P}{2})$. Then $|\psi_{xp}\rangle \in \mathcal{S}'$ for all $(x, p) \in \mathcal{R}$. We can now use an argument analogous to the one leading to Eq. (20) to deduce

$$\Delta'_{\text{ei}} x \Delta'_{\text{ei}} p \geq \frac{\hbar}{2} \left(1 - \frac{2}{L} \Delta'_{\text{ei}} x - \frac{2}{P} \Delta'_{\text{ei}} p \right)$$

which can alternatively be written

$$\left(\Delta'_{\text{ei}} x + \frac{\hbar}{P} \right) \left(\Delta'_{\text{ei}} p + \frac{\hbar}{L} \right) \geq \frac{\hbar}{2} \left(1 + \frac{2\hbar}{LP} \right) \quad (26)$$

If $P \Delta'_{\text{ei}} x$, $L \Delta'_{\text{ei}} p$ and LP are all $\gg \hbar$ we have the approximate relation

$$\Delta'_{\text{ei}} x \Delta'_{\text{ei}} p \gtrsim \frac{\hbar}{2}$$

One expects this approximate form of the retrodictive error relationship to be valid in most situations of practical interest. However, it is not always valid (see the Appendix for a counter example).

Starting from Eqs. (16) and (17) we can derive in a similar manner

$$\begin{aligned} \left(\Delta'_{\text{ei}} x + \frac{\hbar}{P} \right) \left(\Delta'_{\text{d}} p + \frac{\hbar}{L} \right) &\geq \frac{\hbar}{2} \left(1 + \frac{2\hbar}{LP} \right) \\ \left(\Delta'_{\text{ei}} p + \frac{\hbar}{L} \right) \left(\Delta'_{\text{d}} x + \frac{\hbar}{P} \right) &\geq \frac{\hbar}{2} \left(1 + \frac{2\hbar}{LP} \right) \end{aligned} \quad (27)$$

and

$$\begin{aligned} \Delta'_{\text{ef}} x \left(\Delta'_{\text{d}} p + \frac{\hbar}{L} \right) &\geq \frac{\hbar}{2} \\ \Delta'_{\text{ef}} p \left(\Delta'_{\text{d}} x + \frac{\hbar}{P} \right) &\geq \frac{\hbar}{2} \end{aligned} \quad (28)$$

8. CONCLUDING REMARKS

The commonest method of describing the spread of a statistical distribution, in terms of the variance—the method employed in this paper, in other words—is subject to certain limitations. In recent years there has accordingly been some interest in devising alternative approaches. One approach is that involving parameter-based uncertainty relationships [2, 28]. Another approach is that involving entropic uncertainty relationships [19, 20, 21, 29]. It would be interesting to see if either of these approaches can be used to develop the results obtained in this paper.

We should also remark, that in this paper we have made no use of the mathematical theory based on the concept of a POVM, and an unsharp observable [5, 6, 9, 16, 17, 18, 19, 20, 21]. There were certain advantages in proceeding in this way. One advantage was, that it enabled us to circumvent the difficulties which have been identified by Uffink [22, 23]. Also, we share the view of Englert and Wódkiewicz [30], that the underlying intrinsic observables should be regarded as “the heart of the matter.” One of the advantages of the approach adopted here is, that it places the emphasis on these intrinsic observables, as opposed to (in the

words of Englert and Wódkiewicz) a “mathematical representation of the statistical information gathered.” Nevertheless, the theory of POVM’s is clearly an important, and very powerful way of analysing simultaneous measurement processes. We certainly do not mean to set up the approach taken in this paper as an *alternative* to the approach based on POVM’s. We merely wish to stress the point made by Englert and Wódkiewicz, that POVM’s and unsharp observables should be regarded as secondary mathematical constructs, rather than as fundamental physical concepts which need to be posited from the outset. We hope to return to this question in a future publication, in which we will show how the concept of an unsharp observable naturally emerges from the approach taken in this paper.

APPENDIX

The purpose of this appendix is to explain why we defined the errors and disturbances by taking the supremum over every normalised initial system state, as in Eqs. (11–13), or a subset of them, as in Eqs. (23–25). The reason is, that there exist processes such that (for example)

$$\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Xi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle \langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle = 0$$

for certain choices of initial system state $|\psi\rangle$ and initial apparatus state $|\phi_{\text{ap}}\rangle$. It is only when one takes the appropriate supremum that one gets the inequalities of Eqs. (21) and (22) or Eqs. (26–28).

Consider, for example, the measurement interaction described by the evolution operator

$$\hat{U} = \exp \left[-\frac{i\pi}{2\hbar} (\hat{x}\hat{\pi}_{\text{X}} - \hat{\mu}_{\text{X}}\hat{p}) \right]$$

where $\hat{\pi}_{\text{X}}$ is a momentum canonically conjugate to the pointer observable $\hat{\mu}_{\text{X}}$. $\hat{U}$ is a rotation operator in $xp\mu_{\text{X}}\pi_{\text{X}}$ space. It takes $\hat{\mu}_{\text{X}}$ onto $\hat{x}$ and $\hat{x}$ onto $-\hat{\mu}_{\text{X}}$:

$$\begin{pmatrix} \hat{x}_{\text{f}} \\ \hat{\mu}_{\text{Xf}} \end{pmatrix} = \hat{U}^\dagger \begin{pmatrix} \hat{x} \\ \hat{\mu}_{\text{X}} \end{pmatrix} \hat{U} = \begin{pmatrix} \cos \frac{\pi}{2} & -\sin \frac{\pi}{2} \\ \sin \frac{\pi}{2} & \cos \frac{\pi}{2} \end{pmatrix} \begin{pmatrix} \hat{x} \\ \hat{\mu}_{\text{X}} \end{pmatrix} = \begin{pmatrix} -\hat{\mu}_{\text{X}} \\ \hat{x} \end{pmatrix}$$

Similarly

$$\begin{pmatrix} \hat{p}_{\text{f}} \\ \hat{\pi}_{\text{Xf}} \end{pmatrix} = \begin{pmatrix} -\hat{\pi}_{\text{X}} \\ \hat{p} \end{pmatrix}$$

$\hat{\mu}_{\text{P}}$ is unaffected by the interaction. Referring back to the definitions, Eqs. (8-10), we deduce

$$\begin{array}{lll} \hat{\epsilon}_{\text{Xi}} = 0 & \hat{\epsilon}_{\text{Xf}} = \hat{\mu}_{\text{X}} + \hat{x} & \hat{\delta}_{\text{X}} = -\hat{\mu}_{\text{X}} - \hat{x} \\ \hat{\epsilon}_{\text{Pi}} = \hat{\mu}_{\text{P}} - \hat{p} & \hat{\epsilon}_{\text{Pf}} = \hat{\mu}_{\text{P}} + \hat{\pi}_{\text{X}} & \hat{\delta}_{\text{P}} = -\hat{\pi}_{\text{X}} - \hat{p} \end{array}$$

Since $\hat{\mu}_{\text{Xf}} = \hat{x}_{\text{i}}$ the process effects a perfectly accurate retrodiction of position, and this is reflected in the fact that $\Delta_{\text{ei}}x = 0$. On the other hand the momentum pointer is unaffected by the interaction: $\hat{\mu}_{\text{Pf}} = \hat{\mu}_{\text{Pi}}$. This means that the process is not really measuring the momentum at all. We accordingly find $\Delta_{\text{ei}}p = \infty$. If we use the alternative definition of Eq. (23) then we find

$$\Delta'_{\text{ei}}p \geq \frac{P}{2}$$

—which is again consistent with the fact, that so far as momentum is concerned, the process hardly counts as a measurement. Nevertheless, from the fact that

$$\langle \psi \otimes \phi_{\text{ap}} | \hat{\epsilon}_{\text{Pi}}^2 | \psi \otimes \phi_{\text{ap}} \rangle = (\Delta \mu_{\text{P}})^2 + (\Delta p)^2 + \left(\langle \phi_{\text{ap}} | \hat{\mu}_{\text{P}} | \phi_{\text{ap}} \rangle - \langle \psi | \hat{p} | \psi \rangle \right)^2$$

we see, that by appropriately choosing $|\psi\rangle$ and $|\phi_{\text{ap}}\rangle$, $\langle \hat{\epsilon}_{\text{Pi}}^2 \rangle$ can be made arbitrarily small. Moreover, the product $\langle \hat{\epsilon}_{\text{Xi}}^2 \rangle \langle \hat{\epsilon}_{\text{Pi}}^2 \rangle$ will be zero whenever $\langle \hat{\epsilon}_{\text{Pi}}^2 \rangle$ is finite.

It is not surprising that $\langle \hat{\epsilon}_{\text{Pi}}^2 \rangle$ is small for certain choices of initial state. Consider, for example, the classical situation, where one has a classical ammeter whose needle is stuck at the 1 amp position. Then the meter will, of course, give exactly the right reading if one uses it to measure a 1 amp current.

REFERENCES

- [1] W. Heisenberg, Z. Phys. **43**, 172 (1927); translation in *Quantum Theory and Measurement*, edited by J. A. Wheeler and W. H. Zurek (Princeton University Press, Princeton, NJ, 1983). Also see W. Heisenberg, *The Physical Principles of the Quantum Theory*, translated by C. Eckart and F.C. Hoyt (University of Chicago Press, Chicago, 1930; Dover Publications, New York, 1949).
- [2] J. Hilgevoord and J. Uffink, in *Sixty Two Years of Uncertainty*, edited by A. I. Miller (Plenum Press, New York, 1990).
- [3] D. Bohm, *Quantum Theory* (Prentice Hall, New York, 1951).
- [4] L. F. Ballentine, Rev. Mod. Phys. **42**, 358 (1970).
- [5] E. Prugovečki, *Stochastic Quantum Mechanics and Quantum Space-time* (Reidel, Dordrecht, 1984), and references therein.
- [6] P. Busch, Int. J. Theor. Phys. **24**, 63 (1985).
- [7] K. Wódkiewicz, Phys. Lett. A **124**, 207 (1987).
- [8] M. G. Raymer, Am. J. Phys. **62**, 986 (1994).
- [9] W. M. de Muynck, W. de Baere and H. Martens, Found. Phys. **24**, 1589 (1994).
- [10] E. Arthurs and J. L. Kelly, Bell Syst. Tech. J. **44**, 725 (1965).
- [11] E. Arthurs and M. S. Goodman, Phys. Rev. Lett. **60**, 2447 (1988).
- [12] S. L. Braunstein, C. M. Caves and G. J. Milburn, Phys. Rev. A **43**, 1153 (1991); S. Stenholm, Ann. Phys. (N.Y.) **218**, 233 (1992); W. L. Power, S. M. Tan and M. Wilkens, J. Mod. Opt., **44**, 2591 (1997).
- [13] U. Leonhardt and H. Paul, J. Mod. Opt. **40**, 1745 (1993); Phys. Rev. A **48**, 4598 (1993); P. Törma, S. Stenholm and I. Jex, Phys. Rev. A **52**, 4812 (1995).
- [14] U. Leonhardt and H. Paul, Prog. Quant. Electr. **19**, 89 (1995).
- [15] U. Leonhardt, *Measuring the Quantum State of Light* (Cambridge University Press, Cambridge, 1997).
- [16] P. Busch, M. Grabowski and P. J. Lahti, *Operational Quantum Physics* (Springer-Verlag, Berlin, 1995).
- [17] E. B. Davies, *Quantum Theory of Open Systems* (Academic Press, New York, 1976).
- [18] A. S. Holevo, *Probabilistic and Statistical Aspects of Quantum Theory* (North-Holland, Amsterdam, 1982).
- [19] P. Busch and P. J. Lahti, Found. Phys. **19**, 633 (1989).
- [20] H. Martens and W. M. de Muynck, Found. Phys. **20**, 255; 357 (1990); J. Phys. A **25**, 4887 (1992).
- [21] M. Ban, Int. J. Theor. Phys. **36**, 2583 (1997).
- [22] J. Uffink, Int. J. Theor. Phys. **33**, 199 (1994).
- [23] D. M. Appleby, report no. QMW-PH-98-11, xxx.lanl.gov quant-ph/9803046. To appear in Int. J. Theor. Phys.
- [24] V. B. Braginsky and F. Ya. Khalili, *Quantum Measurement*, edited by K. S. Thorne (Cambridge University Press, Cambridge, 1992).
- [25] H. Margenau, Phil. Sci. **25**, 23 (1958); E. Prugovečki, Found. Phys. **3**, 3 (1973), and J. Math. Phys. **17**, 1673 (1976).
- [26] U. Leonhardt and H. Paul, Opt. Commun. **119**, 296 (1995).

- [27] D. M. Appleby, report no. QMW-PH-98-12, xxx.lanl.gov quant-ph/9803047. Submitted to J. Phys. A.
- [28] S. L. Braunstein, C. M. Caves and G. J. Milburn, Ann. Phys. NY **247**, 135 (1996).
- [29] V. Bužek, C. H. Keitel and P. L. Knight, Phys. Rev. A **51**, 2575; 2594 (1995).
- [30] B-G. Englert and K. Wódkiewicz, Phys. Rev. A **51**, R2661 (1995).